

ICM of America  
Internet Sales  
877-494-5793



#### **XLT-17 Liquid Leak Detector**

Fisher's XLT-17 is a liquid leak detector that finds leaks in four easy steps: by electronically amplifying leak sounds, selectively filtering out noise, isolating the leak sound, and leading the operator to the source of the leak.

#### **FEATURES**

- Detects and pinpoints liquid leaks in pipes
- 4 Frequency Filters: Low Pass, High Pass, Band Pass and All Pass
- Last setting memory feature
- Touch-control keypad
- Shielded sensor for reduced response to outside noise
- Improved headset for clearer sound response
- Automatic battery test – real time voltage level
- Operates on two 9 volt batteries
- Compact control box that can be worn around the neck or over the shoulder with an attachable strap
- Heavy duty carrying case

#### **SPECIFICATIONS**

- Operating Frequency:
  - 60 Hz – 6 kHz, Gain = 60 db
  - 20 Hz – 60 Hz, Gain > 55 dB
- Filter Types and Frequency Ranges:
  - All Pass: 60 Hz to 6 kHz
  - Low Pass: Adjustable cut-off frequency from 150 Hz to 2.4 kHz
  - High Pass: Adjustable pass band frequency from 150 Hz to 2.4 kHz
  - Band Pass: Adjustable center frequency from 150 Hz to 2.4 kHz
- Output Indications:
  - Audio: High performance headphones (64 ohms)
  - Visual: LCD bar graph and 2-digit numeric display
- Grade of Protection: Splash Proof
- Battery Test: Automatic, real time battery level indicator
- Battery Quantity/Type: 2 / 9V Alkaline
- Battery Life: 50 Hours (approximately)
- Carrying Case Dimensions: 21"x 6"x 14" (53.3 x 15.2 x 35.6 cm)
- Weight: 10 lbs. (4.5 kg) (unit in carrying case)